



# Wireless N 150 Ultra Mini USB Adapter

Model #: AWLL5088



## Quick Installation Guide for MAC OS X



Rev. 1.0

# 1. Install Wireless N USB Adapter


This section provides instructions on how to install the **Wireless N 150 Ultra Mini USB Adapter**. The driver is installed along with the utility.

**Step 1** Insert the USB adapter into an available USB port of the computer. Insert the provided CD into the CD drive.


**Step 2** Explore the CD content, go to **MAC** folder, then further to the driver folder that matches to your MAC OS and CPU (Intel or PowerPC) version. Double click on **Installer.pkg** to start installing the driver & utility.



**Step 3 Introduction:** The “Install Wireless N USB Adapter Driver” window will pop up. Click **Continue**.




**Step 4 Read Me:** Read the instruction of installation. Click **Continue** to begin the installation.




**Step 5 License:** Click **Continue**.



**Step 6** Click **Agree** to install.




**Step 7 Installation Type:** click **Install** to perform a standard installation.



**Step 8** Enter your password and click **OK**.




**Step 9** Click **Continue Installation**.



**Step 10 Install:** Wait while the software is being installed.

**Step 11 Summary:** Click **Restart** to restart your computer.



Go to Chapter 2 after the computer is restarted.


## 2. Connect to Wireless Network

### 2.1 Enable the Wireless USB Adapter

This section describes how to enable your wireless USB adapter before you can connect to a wireless network.


**For 10.4/10.5 MAC users:**

**Step 1** Go to **System Preferences > Network**, select **Network Port Configurations** from Show.






**Step 2** Check the Ethernet Adaptor (Wireless N USB Adapter) and uncheck AirPort. Click **Apply Now**.



**For 10.6 MAC users:**


After the computer is restarted, you will see this notice popped up on your screen to inform you that you need to enable the wireless card.






**Step 1** Go to **System Preferences > Network**.

You should see Wireless N USB Adapter in the list, if not, please click “+” to add a new network interface.



**Step 2** Select Wireless N USB Adapter from the Interface drop-down list and click **Create**. Click **Apply** to save the settings.




## 2.2 Connect to Wireless Network

This section describes how to connect your wireless USB adapter to a wireless network.


**Step 1** Wireless Network Utility should automatically pop up on your screen after rebooting your computer; if not, open the Wireless Monitor utility by clicking on its icon in the system tray.



The Wireless Network Utility will appear on your monitor.



**Step 2** Click the **Available Network** tab, select the **SSID** (Network Name) of the wireless network you wish to connect to, and click **Add to Profile**.




If the network that you are attempting to connect does not have encryption enabled, you will receive a warning about connecting to an unsecured network. Click **OK** to complete the connection. Go to Step 4.

**Step 3** Enter the network security key of your wireless router or AP into **Network key** and **Confirm network key** boxes.

The image shows a 'Profile Properties' dialog box with the following fields and options:

- Profile Name : AP00-Outdoor
- SSID : AP00-Outdoor
- ☐ This is a computer-to-computer (AdHoc) network; wireless access points are not used.
- Channel : 1: 2412 MHz
- Wireless Network Security Properties
  - This network requires a key for the following :
  - Network Authentication : WPA2\_PSK
  - Data Encryption : AES
  - ☐ ASCII
  - Network key : [Red box]
  - Confirm network key : [Red box]
  - Key index (advanced) : 1
- Buttons: Cancel, OK [Red box]

**Step 4** The connection is now established. You can check the status of your connection under “Link Status” tab. The Connection should be **Connected**, and there should be a blue bar displaying the Signal Strength.



Congratulations! You have now successfully connected to the wireless network. You may refer to the User Manual in this Installation CD for detailed instructions of other advanced features of Wireless N USB Adapter.

## Technical Support

E-mail: [support@airlink101.com](mailto:support@airlink101.com)

Toll Free: 1-888-746-3238

Web Site: [www.airlink101.com](http://www.airlink101.com)

\*Theoretical maximum wireless signal rate derived from IEEE standard 802.11g and draft 802.11n specifications. Actual data throughput will vary. Network conditions and environmental factors, including volume of network traffic, building materials and construction, mix of wireless products used, radio frequency interference (e.g., cordless telephones and microwaves) as well as network overhead lower actual data throughput rate. Compatibility with 802.11n devices from other manufactures is not guaranteed. Specifications are subject to change without notice. Photo of product may not reflect actual content. All products and trademarks are the property of their respective owners.  
Copyright ©2010 Airlink101®